

Mapping worksheet for instruments that contain "PJ" pickup configuration

Lets you get 21 Pickup Tones. (see our website Document Library for connection information)

Switch Legend

- SW1: Turns on Coil-1. D=Down (normal-phase), U=Up (reverse-phase), blank=Off (middle).
When On by itself, Down or Up produces the same pickup tone.
- SW2: Turns on Coil-2 & Coil-3. D=Down, blank=Off (middle). (Up offers no function)
- SW3: Changes phase of Coil-2 & Coil-3. D=Down (normal-phase), U=Up (reverse-phase).
- SW4: Controls if Coils-1, -2, -3 can be in Parallel (Down) or in Series (Up) connection.
- SW5: Controls if Coil-2 & Coil-3 are in Parallel (Down) or in Series (Up) connection.

Transfer your "favorite" three pickup tone switch positions to Fav-1, Fav-2 and Fav-3.

	SW3	SW5	SW2	SW4	SW1	What the Pickup tone sounds like to you
Fav-1						
Fav-2						
Fav-3						
1				D	D/U	
2	D	D	D	D		
3	U	D	D	D		
4	D	U	D	D		
5	U	U	D	D		
6	D	D	D	D	D	
7	U	D	D	D	D	
8	D	U	D	D	D	
9	U	U	D	D	D	
10	D	D	D	D	U	
11	U	D	D	D	U	
12	D	U	D	D	U	
13	U	U	D	D	U	
14	D	D	D	U	D	
15	U	D	D	U	D	
16	D	U	D	U	D	
17	U	U	D	U	D	
18	D	D	D	U	U	
19	U	D	D	U	U	
20	D	U	D	U	U	
21	U	U	D	U	U	

Coil-1: Bridge "Jazz Bass" Pickup

Coil-2: Middle "P Bass" Pickup

Coil-3: Neck "P Bass" Pickup